

**6050-2 3332F**

# USB PD Dual-channel Test System



**Basic version**



**Standard version**



**Value version**



**Complete version**

## Feature

- 2 sets of U.U.T can be tested at the same time to improve test efficiency and save test time and cost
- Select the required device configuration version (Basic / Standard / Added Value / Full version) according to product testing requirements
- In addition to supporting USB PD, also supports QC2.0 / QC3.0 / PE+ / PE+2.0
- Highly cost-effective, fully functional modular design test system
- Operating environment of Windows 7 or higher (included)
- Open architecture software platform
  1. Support related hardware expansion
  2. Edit test item function
  3. Edit test program function
  4. Edit statistical analysis report function
  5. Online instrument control function
  6. User authorization settings
  7. Support Bar Code Reader

# 6050-2 ( 3332F ) USB PD DUAL-CHANNEL TEST SYSTEM

## USB PD Test items and equipment configuration table

| Test items                        | Instrument Equipment     |                           |                  |                                |                         |                         |                                  |             |
|-----------------------------------|--------------------------|---------------------------|------------------|--------------------------------|-------------------------|-------------------------|----------------------------------|-------------|
|                                   | APS-7000<br>AC<br>Source | 99094<br>QC<br>Controller | 3332F<br>DC Load | 4032 - PD<br>Timing &<br>Noise | 4015A<br>Power<br>Meter | 4013A<br>Power<br>Meter | PFR-100L<br>D.C. Power<br>Supply | 5303<br>AVR |
| <b>USB PD USB PD Performances</b> |                          |                           |                  |                                |                         |                         |                                  |             |
| USB PD Source / Sink Profile      | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| USB PD Power Data Object (PDO)    | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| Positive Voltage Transitions      | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| Negative Voltage Transitions      | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| Hard Reset                        | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| USB Type C Cable unplug           | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| <b>Output Performances</b>        |                          |                           |                  |                                |                         |                         |                                  |             |
| Output Voltage                    | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| Output Current                    | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| Dynamic Load (Vpeak +/-)          | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| Average Efficiency                | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| Ripple Voltage                    | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| <b>Input Characteristics</b>      |                          |                           |                  |                                |                         |                         |                                  |             |
| Input RMS Current                 | ✓                        | ✓                         | ✓                |                                | ✓                       | ✓                       |                                  |             |
| Input Frequency                   | ✓                        | ✓                         | ✓                |                                | ✓                       | ✓                       |                                  |             |
| Input Power                       | ✓                        | ✓                         | ✓                |                                | ✓                       | ✓                       |                                  |             |
| No Load Power Consumption         | ✓                        | ✓                         | ✓                |                                | ✓                       | ✓                       |                                  |             |
| Input Power Factor                | ✓                        | ✓                         | ✓                |                                | ✓                       | ✓                       |                                  |             |
| Input Voltage Sag                 | ✓                        | ✓                         | ✓                | ✓                              | ✓                       | ✓                       |                                  |             |
| Current Harmonics                 | ✓                        | ✓                         | ✓                |                                | ✓                       |                         |                                  |             |
| Input Inrush Current              | ✓                        | ✓                         | ✓                |                                | ✓                       | ✓                       |                                  | ✓           |
| <b>Regulation Tests</b>           |                          |                           |                  |                                |                         |                         |                                  |             |
| Line Regulation                   | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| Load Regulation                   | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| Combine Regulation                | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| <b>Timing &amp; Transient</b>     |                          |                           |                  |                                |                         |                         |                                  |             |
| Turn ON (Set-Up) Time             | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| Turn OFF (Hold-Up) Time           | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| Rise Time                         | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| Fall Time                         | ✓                        | ✓                         | ✓                | ✓                              |                         |                         |                                  |             |
| <b>Protection Tests</b>           |                          |                           |                  |                                |                         |                         |                                  |             |
| Short Circuit                     | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| OV Protection                     | ✓                        | ✓                         | ✓                |                                |                         |                         | ✓                                |             |
| OC Protection                     | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |
| OP Protection                     | ✓                        | ✓                         | ✓                |                                |                         |                         |                                  |             |

## USB PD Dual-channel test system quick selection table

| Test items                     | 6050 USB PD Dual-channel test system quick selection table |                                  |                                  |                                  |
|--------------------------------|--|----------------------------------|----------------------------------|----------------------------------|
|                                | 6050-2-A1<br>Basic version                                 | 6050-2-B1<br>Standard version    | 6050-2-C1<br>Value Version       | 6050-2-D1<br>Complete version    |
| <b>USB PD Performances</b>     |  |                                  |                                  |                                  |
| USB PD Source / Sink Profile   | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| USB PD Power Data Object (PDO) | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Positive Voltage Transitions   |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Negative Voltage Transitions   |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Hard Reset                     |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| USB Type C Cable unplug        |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| <b>Output Performances</b>     |  |                                  |                                  |                                  |
| Output Voltage                 | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Output Current                 | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Dynamic Load (Vpeak +/-)       |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Average Efficiency             | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Ripple Voltage                 |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| <b>Input Characteristics</b>   |  |                                  |                                  |                                  |
| Input RMS Current              | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Input Frequency                | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Input Power                    | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| No Load Power Consumption      | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Input Power Factor             | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Input Voltage Sag              | <input type="radio"/>                                      | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Current Harmonics              |  |                                  | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Input Inrush Current           |  |                                  |                                  | <input checked="" type="radio"/> |
| <b>Regulation Tests</b>        |  |                                  |                                  |                                  |
| Line Regulation                | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Load Regulation                | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Combine Regulation             | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| <b>Timing &amp; Transient</b>  |  |                                  |                                  |                                  |
| Turn ON (Set-Up) Time          |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Turn OFF (Hold-Up) Time        |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Rise Time                      |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| Fall Time                      |  | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| <b>Protection Tests</b>        |  |                                  |                                  |                                  |
| Short Circuit                  | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| OV Protection                  |  |                                  |                                  | <input checked="" type="radio"/> |
| OC Protection                  | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |
| OP Protection                  | <input checked="" type="radio"/>                           | <input checked="" type="radio"/> | <input checked="" type="radio"/> | <input checked="" type="radio"/> |

△ Only provide Input Voltage Sag capability

6050-2-A1 Single Output USB PD basic version :

the dual-channel test system configuration is as shown in the table, just needs APS-7000 series AC Source, 3302F + 3332F series and 99094-2 Quick Charge Controller and 4013A-2 Power Meter. The basic version system configuration is shown below.




→ 3302F + 3332F DC Load

→ 99094-2 Quick Charge Controller

→ 4013A-2 Power Meter

→ APS-7000 series AC Sources

**6050-2-A1 Basic version dual- channel test system block diagram**



6050-2-A1 Dual Channel Test System Configuration

**6050-2-A1 Basic version dual- channel test system test items are as follows**

| <b>USB PD Performances</b>     |
|--------------------------------|
| USB PD Source / Sink Profile   |
| USB PD Power Data Object (PDO) |

| <b>Output Performances</b> |
|----------------------------|
| Output Voltage             |
| Output Current             |
| Average Efficiency         |

| <b>Regulation Tests</b> |
|-------------------------|
| Line Regulation         |
| Load Regulation         |
| Combine Regulation      |

| <b>Input Characteristics</b> |
|------------------------------|
| Input RMS Current            |
| Input Frequency              |
| Input Power                  |
| No Load Power Consumption    |
| Input Power Factor           |

| <b>Protection Tests</b> |
|-------------------------|
| Short Circuit           |
| OC Protection           |
| OP Protection           |

**6050-2-A1 Basic version dual- channel test system equipment configuration table**

| <b>Model</b>  | <b>Quantity</b>                   |
|---|-----------------------------------|
| APS-7000 Series Programmable Linear AC Power Sources                | 1                                 |
| 3302F 1CH Mainframe   | 1                                 |
| 3332F 80V/24A/120Wx 2 DC Load Module                                | 1                                 |
| 99094-2 Quick Charge Controller ( dual-channel )                    | 1                                 |
| 4013A-2 Power Meter ( dual-channel )                                | 1                                 |
| 6050 system software  | 1                                 |
| System Controller (PC)  | 1                                 |
| CP-104EL-A 1:4 High Speed RS-232 Card                               | 1                                 |
| Uport 1410 USB to RS-232 4 Port For Note Book                       | 0                                 |
| <b>System Specifications ( PC or Note Book )</b>                    |                                   |
| CPU   | i5-3470(3.2GHz) or faster         |
| SRAM  | 256KB                             |
| DRAM  | 4GB or higher                     |
| Hard Driver   | 500GB or higher                   |
| CD-ROM  | 40X or faster                     |
| Monitor   | 22"                               |
| KeyBoard  | 101 Keys                          |
| I/O   | Mouse/Print Port                  |
| System Interface  | RS-232                            |
| System I/O  | 1:4 or 1:8 High Speed RS-232 Card |
| ○ The system device should use this interface when using Note Book. |                                   |


OS : Windows 7.0 or latest version

6050-2-B1 Standard version dual-channel test system is consisted of basic version :  
 by adding 4032-PD Dual Timing & Noise Meter can increase USB PD characteristics and timing  
 and transient testing  
 The standard version system configuration is shown below.



- 60102+4032-PD+3332F DC Load
- 99094-2 Quick Charge Controller
- 4013A-2 Power Meter
- APS-7000 series AC Sources

**6050-2-B1 Standard version dual-channel test system block diagram**



6050-2-B1 Dual Channel Test System Configuration

**6050-2-B1 Standard version by adding 4031-PD x 2 and 99094-2 two channels Quick Charger Controller can increase the test items as shown in the block below.**

| <b>USB PD Performances</b>   |
|------------------------------|
| Positive Voltage Transitions |
| Negative Voltage Transitions |
| Hard Reset                   |
| USB Type C Cable unplug      |

| <b>Timing &amp; Transient</b> |
|-------------------------------|
| Turn ON (Set-Up) Time         |
| Turn OFF (Hold-Up) Time       |
| Rise Time                     |
| Fall Time                     |

| <b>Output Performances</b> |
|----------------------------|
| Dynamic Load (Vpeak +/-)   |
| Ripple Voltage             |

| <b>Input Characteristics</b> |
|------------------------------|
| Input Voltage Sag            |

**6050-2-B1 Standard version dual-channel test system equipment configuration table**

| <b>Model</b>  | <b>Quantity</b>                   |
|---|-----------------------------------|
| APS-7000 Series Programmable Linear AC Power Sources                | 1                                 |
| 60102 2CH Mainframe ; 4032-PD, 3332F                                | 1                                 |
| 3332F 80V/24A/120W x 2 DC Load Module                               | 1                                 |
| 4032-PD Dual Timing & Noise Meter for PD                            | 1                                 |
| 99094-2 Quick Charger Controller ( dual-channel )                   | 1                                 |
| 4013A-2 Power Meter ( dual-channel )                                | 1                                 |
| 6050 system software  | 1                                 |
| System Controller (PC)  | 1                                 |
| CP-104EL-A 1:4 High Speed RS-232 Card                               | 1                                 |
| Uport 1410 USB to RS-232 4 Port For Note Book                       | 0                                 |
| <b>System Specifications ( PC or Note Book )</b>                    |                                   |
| CPU   | i5-3470(3.2GHz) or faster         |
| SRAM  | 256KB                             |
| DRAM  | 4GB or higher                     |
| Hard Driver   | 500GB or higher                   |
| CD-ROM  | 40X or faster                     |
| Monitor   | 22"                               |
| KeyBoard  | 101 Keys                          |
| I/O   | Mouse / Print Port                |
| System Interface  | RS-232                            |
| System I/O  | 1:4 or 1:8 High Speed RS-232 Card |
| ○ The system device should use this interface when using Note Book. |                                   |

OS : Windows 7.0 or latest version

6050-2-C1 Value version (Standard version + Input current harmonic) dual-channel test system :  
 Changing 4013A-2 to 4015A-2 power meter with Harmonic can increase the current harmonic  
 Harmonics test.

The value version system configuration is shown below.




→ 60102+4032-PD+3332F DC Load

→ 99094-2 Quick Charge Controller

→ 4015A-2 Power Meter with Harmonic

→ APS-7000 series AC Sources

**6050-2-C1 Value version dual-channel test system block diagram**



6050-2-C1 Dual Channel Test System Configuration

**6050-2-C1 Value version dual-channel test system : Changing 4013A-2 to 4015A-2 power meter can increase the test items as shown in the following green block**

|                              |
|------------------------------|
| <b>Input Characteristics</b> |
| Current Harmonics            |

**6050-2-C1 Value version dual-channel test system equipment configuration table**

| <b>Model</b>  | <b>Quantity</b>                   |
|---|-----------------------------------|
| APS-7000 Series Programmable Linear AC Power Sources                | 1                                 |
| 60102 2CH Mainframe; 4032-PD, 3332F                                 | 1                                 |
| 3332F 80V/24A/120Wx 2 DC Load Module                                | 1                                 |
| 4032-PD Dual Timing & Noise Meter for PD                            | 1                                 |
| 4015A-2 Power Meter with Harmonic ( dual-channel )                  | 1                                 |
| 99094-2 Quick Charger Controller ( dual-channel )                   | 1                                 |
| 6050 system software  | 1                                 |
| System Controller (PC)  | 1                                 |
| CP-104EL-A 1:4 High Speed RS-232 Card                               | 1                                 |
| Uport 1410 USB to RS-232 4 Port For Note Book                       | 0                                 |
| <b>System Specifications ( PC or Note Book )</b>                    |                                   |
| CPU   | i5-3470(3.2GHz) or faster         |
| SRAM  | 256KB                             |
| DRAM  | 4GB or higher                     |
| Hard Driver   | 500GB or higher                   |
| CD-ROM  | 40X or faster                     |
| Monitor   | 22"                               |
| KeyBoard  | 101 Keys                          |
| I/O   | Mouse / Print Port                |
| System Interface  | RS-232                            |
| System I/O  | 1:4 or 1:8 High Speed RS-232 Card |
| ○ The system device should use this interface when using Note Book. |                                   |

OS : Windows 7.0 or latest version

6050-2-D1 The Complete version (Standard version + Input Current Harmonics + Input Inrush Current) dual-channel test system : adds 5303 AVR and PFR-100L two channels OVP Source to increase Input Inrush Current and over voltage protection tests.

The Complete version system configuration is shown below.



→ 60102+4032-PD+3332F DC Load

→ 99094-2 Quick Charge Controller


→ PFR-100Lx2 D.C. Power Supply

→ 4015A-2 Power Meter with Harmonic

→ 5303 AVR for Inrush Current

→ APS-7000 series AC Sources

**6050-2-D1 Complete version dual-channel test system block diagram**



6050-2-D1 Dual Channel Test System Configuration

**6050-2-D1 Complete version by adding 5303 and PFR-100L, the following items can be added to the test item**

**Input Characteristics**

Input Inrush Current

**Protection Tests**

OV Protection

**6050-2-D1 Complete version dual-channel equipment configuration table**

| Model   | Quantity                          |
|---|-----------------------------------|
| APS-7000 Series Programmable Linear AC Power Sources                | 1                                 |
| 60102 2CH Mainframe; 4032-PD, 3332F                                 | 1                                 |
| 3332F 80V/24A/120Wx 2 DC Load Module                                | 1                                 |
| 4032-PD Dual Timing & Noise Meter for PD                            | 1                                 |
| 4015A-2 Power Meter with Harmonic ( dual-channel )                  | 1                                 |
| PFR-100L Fanless Multi-Range D.C. Power Supply                      | 2                                 |
| 5303 3KVA AVR   | 1                                 |
| 99094-2 Quick Charger Controller ( dual-channel )                   | 1                                 |
| 6050 system software  | 1                                 |
| System Controller (PC)  | 1                                 |
| CP-104EL-A 1:4 High Speed RS-232 Card                               | 1                                 |
| Uport 1410 USB to RS-232 4 Port For Note Book                       | 0                                 |
| <b>System Specifications ( PC or Note Book )</b>                    |                                   |
| CPU   | i5-3470(3.2GHz) or faster         |
| SRAM  | 256KB                             |
| DRAM  | 4GB or higher                     |
| Hard Driver   | 500GB or higher                   |
| CD-ROM  | 40X or faster                     |
| Monitor   | 22"                               |
| KeyBoard  | 101 Keys                          |
| I/O   | Mouse / Print Port                |
| System Interface  | RS-232                            |
| System I/O  | 1:4 or 1:8 High Speed RS-232 Card |
| ○ The system device should use this interface when using Note Book. |                                   |

OS : Windows 7.0 or latest version

# All Equipment Functions and Specifications List

## APS-7000 Series Programmable Linear AC Power Sources Suitable test item & Specifications

| Model  | APS-7000 Series Programmable Linear AC Power Sources |   |   |                 |
|--|--|---|---|-----------------|
| <b>Suitable Test Item</b>  |  |   |   |                 |
| 1. Input RMS Current<br>2. Input Frequency<br>3. Input Power<br>4. No Load Power Consumption<br>5. Input Power Factor<br>6. Input Voltage Sag<br>7. Line Regulation<br>8. A voltage ON/OFF angle ( 0 ~ 360°) Can be programmed |  |   |   |                 |
| <b>Specifications</b>  | <b>APS-7050</b>                                      | <b>APS-7100</b>   | <b>APS-7200</b>   | <b>APS-7300</b> |
| Power Rating   | 500VA  | 1000VA  | 2000VA  | 3000VA          |
| Voltage Rating   | 0 ~ 155Vrms, 0 ~ 310Vrms                             |   |   |                 |
| Current Rating   | 0~155Vrms  | 4.2A  | 8.4A  | 16.8A           |
|  | 0~310Vrms  | 2.1A  | 4.2A  | 8.4A            |
| Frequency  | 45 ~ 500 Hz  |   |   |                 |
| Angle (ON/OFF)   | 0 ~ 359°   |   |   |                 |
| PQT<IEC 61000-4-11>  | DIP, Interrupt, Variation                            |   |   |                 |
| <b>MEASUREMENT</b>   |  |   |   |                 |
| ACV meter (Vrms)   | 0 ~ 155Vrms, 0 ~ 310Vrms, Auto                       |   |   |                 |
| Voltage (RMS)  | Range  | 0.20~38.75Vrms;38.76~77.50Vrms;77.51~155.0Vrms;155.1~310.0Vrms  |   |                 |
|  | Resolution   | 0.01V at 0.00 ~ 99.99Vrms; 0.1V at 100.0 ~ 310.0Vrms  |   |                 |
|  | Accuracy *4  | ±(0.5% of reading + 2 counts)   |   |                 |
| Frequency  | Range  | 45 ~ 500Hz  |   |                 |
|  | Resolution   | 0.01Hz at 45Hz~99.99Hz ; 0.1Hz at 100Hz~500.0Hz   |   |                 |
|  | Accuracy   | ±0.1Hz  |   |                 |
| Current (RMS)  | Range  | 2.00 ~ 70.00mA ; 60.0 ~ 350.0mA ;<br>0.300 ~ 3.500A ; 3.00 ~ 17.5A  | 0.200 ~ 3.500A ; 3.00 ~ 35.00A  |                 |
|  | Resolution   | 0.01mA, 0.1mA, 0.001A, 0.01A  | 0.001A ; 0.01A  |                 |
|  | Accuracy   | ± (0.6% of reading+5 counts), 2.00~350.0mA ;<br>± (0.5% of reading+5 counts), 0.300~3.500A ;<br>± (0.5% of reading+3 counts),3.000~17.50A | ± (0.5% of reading + 5 counts) , 0.200 ~ 3.500A<br>± (0.5% of reading + 3 counts) , 3.00 ~ 35.00A |                 |
| Current (Peak)   | Range  | 0.0 ~ 70.0A   | 0.0 ~ 140.0A  |                 |
|  | Resolution   | 0.1A  |   |                 |
|  | Accuracy   | ± ( 1% of reading + 1 count )   |   |                 |
| Power (W)  | Resolution   | 0.01W, 0.1W, 1W   | 0.1W, 1W  |                 |
|  | Accuracy   | ± (0.6% of reading+5 counts), 0.20~99.99W ;<br>± (0.6% of reading+5 counts), 100.0~999.9W ;<br>± (0.6% of reading+2 counts), 1000~9999W   | ± (0.6% of reading + 5counts) , 0.2 ~ 999.9W<br>± (0.6% of reading + 2counts) , 1000 ~ 9999W      |                 |
| Apparent (VA)  | Resolution   | 0.01VA, 0.1VA, 1VA  | 0.1VA, 1VA  |                 |
|  | Accuracy   | ±(1% of reading+7 counts), 0.20~99.99VA ;<br>±(1% of reading+7 counts), 100.0~999.9V A ;<br>±(1% of reading+5 counts), 1000~9999VA        | ± (1% of reading + 7 counts) , 0.2 ~ 999.9VA ;<br>± (1% of reading + 5 counts) , 1000 ~ 9999VA    |                 |
| Power Factor   | Resolution   | 0.001   |   |                 |
|  | Accuracy   | ± ( 2% of reading + 2 counts )  |   |                 |
| Frequency meter  | 45 ~ 500Hz   |   |   |                 |
| Interface  | RS-232   |   |   |                 |

Table 1 - Preferred test level and durations for voltage dips

| Class <sup>a</sup>   | Test level and durations for voltage dips(ts) (50 Hz/60 Hz) |                       |  |  |  |
|----------------------|---|-----------------------|--|--|--|
| Class 1              | Case-by-case according to the equipment requirements        |                       |  |  |  |
| Class 2              | 0 % during<br>1/2 cycle                                     | 0 % during<br>1 cycle | 70 % during 25/30 <sup>c</sup> cycles    |  |  |
| Class 3              | 0 % during<br>1/2 cycle                                     | 0 % during<br>1 cycle | 40 % during<br>10/12 <sup>c</sup> cycles | 70 % during<br>25/30 <sup>c</sup> cycles | 80 % during<br>250/300 <sup>c</sup> cycles |
| Class X <sup>b</sup> | X   | X                     | X  | X  | X  |

a Classes as per IEC 61000-2-4 ; see Annex B.

b To be defined by product committee. For equipment connected directly or indirectly to the public network, the levels must not be less severe than Class 2.

c "25/30 cycles" means "25 cycles for 50 Hz test" and "30 cycles for 60 Hz test"

Table 2 - Preferred test level and durations for short interruptions

| Class <sup>a</sup>   | Class <sup>a</sup> Test level and durations for short interruptions (ts) (50 Hz/60 Hz) |
|----------------------|--|
| Class 1              | Case-by-case according to the equipment requirements                                   |
| Class 2              | 0 % during 250/300 <sup>c</sup> cycles   |
| Class 3              | 0 % during 250/300 <sup>c</sup> cycles   |
| Class X <sup>b</sup> | X  |

a Classes as per IEC 61000-2-4 ; see Annex B.

b To be defined by product committee. For equipment connected directly or indirectly to the public network, the levels must not be less severe than Class 2.

c "25/30 cycles" means "25 cycles for 50 Hz test" and "30 cycles for 60 Hz test"

Table 3 - Timing of short-term supply voltage variations

| Voltage test level | Time for decreasing voltage (td) | Time at reduced voltage (ts) | Time for increasing voltage (ti) (50 Hz/60 Hz) |
|--------------------|----------------------------------|------------------------------|--|
| 70%                | Abrupt                           | 1 cycle                      | 25/30 <sup>b</sup> cycles                      |
| X <sup>a</sup>     | X <sup>a</sup>                   | X <sup>a</sup>               | X <sup>a</sup>                                 |

a To be defined by product committee.

b "25/30 cycles" means "25 cycles for 50 Hz test" and "30 cycles for 60 Hz test".

## 3332F Dual DC E-Load List of Specification and applicable features

| Model  | 3332F DC E-Load   |                 |
|--|---|-----------------|
| <b>Applicable test function</b>  |   |                 |
| 1. Output Voltage<br>2. Output Current<br>3. Dynamic Load<br>4. Efficiency | 5. Average Efficiency<br>6. Short Circuit<br>7. OC Protection<br>8. OP Protection |                 |
| <b>Specifications</b>  |   |                 |
| <b>Power</b>   | 120W x 2  |                 |
| <b>Current</b>   | 24A   |                 |
| <b>Voltage</b>   | 80V   |                 |
| <b>Constant Current Mode</b>   |   |                 |
| <b>Range</b>   | 0 ~ 2.4A  | 0 ~ 24A         |
| <b>Constant Resistance Mode</b>  |   |                 |
| <b>Range</b>   | 3.33Ω ~ 199.80KΩ  | 0.0333Ω ~ 3.33Ω |
| <b>Constant Voltage Mode</b>   |   |                 |
| <b>Range</b>   | 0 ~ 6V  | 0 ~ 80V         |
| <b>Constant Power Mode</b>   |   |                 |
| <b>Range</b>   | 0 ~ 12W   | 0 ~ 120W        |
| <b>Dynamic Mode</b>  |   |                 |
| <b>Timing</b>  |   |                 |
| Thigh & Tlow   | 0.050 ~ 9.999 / 99.99 / 999.9 / 9999mS  |                 |
| Resolution   | 0.001 / 0.01 / 0.1 / 1mS  |                 |
| Slew rate  | 1.6 ~ 100mA/uS  | 16 ~ 1000mA/uS  |
| Accuracy   | ± (5% of Setting) ±10uS   |                 |
| <b>Measurement</b>   |   |                 |
| <b>Voltage Read Back</b>   |   |                 |
| Range (5 Digital)  | 6V  | 81V             |
| <b>Current Read Back</b>   |   |                 |
| Range (5 Digital)  | 2.4A  | 24A             |
| Resolution   | 0.0001A   | 0.001A          |
| Current Monitor  | FULL SCALE 10V  |                 |
| Current Programming Input  | FULL SCALE 10V  |                 |
| Programmable Short   | BUILT-IN  |                 |
| Load ON Voltage  | 0.1 ~ 25V   |                 |
| Accuracy   | 1% of (Setting + Range)   |                 |
| Load OFF Voltage   | 0 ~ 25V   |                 |
| Accuracy   | 0.025% of (Setting + Range)   |                 |
| Typical Short Resistance   | 0.02 Ω  |                 |
| Maximum Short Current  | 30 A  |                 |
| <b>Operating range</b>   |   |                 |
| Temperature  | 0 ~ +40°C   |                 |
| Humidity   | 20 ~ 85%rh  |                 |

## 4032-PD List of Specification and applicable features

| Model   | 4032-PD Noise & Timing Analyzer Module |  |                             |
|---|--|--|-----------------------------|
| <b>Applicable test function</b>   |  |  |                             |
| 1. Positive Voltage Transitions<br>2. Negative Voltage Transitions<br>3. Hard Reset<br>4. USB Type C Cable Unplug<br>5. Ripple Voltage<br>6. Dynamic Load Vpeak +/- Measure |  | 7. Input Voltage Sag<br>8. Turn ON(Set-Up) Time<br>9. Turn OFF(Hold-Up) Time<br>10. Rise Time<br>11. Fall Time |                             |
| <b>Specifications</b>   |  |  |                             |
| <b>No. of input channel</b>   |  | <b>1</b>   |                             |
| <b>Timing Measurement</b>   |  | <b>Ripple Measurement</b>  |                             |
| <b>Set-up / Hold-up / Rise / Fall Time</b>  |  | <b>Band Width</b>  | 0 ~ 100 KHz                 |
| <b>Voltage range</b>  | 0 ~ 10/30 Vdc                          | <b>Voltage range</b>   | 0 ~ 10 / 30 Vdc             |
| <b>Current range</b>  | *(1/4F.S.)/(F.S.) Adc                  | <b>Measurement range</b>   | 0 ~ 0.4 / 1 Vp-p            |
| <b>Timing range</b>   | 1 Sec/2 Sec/4 Sec/8 Sec/16 Sec         | <b>Resolution</b>  | 0.001 / 0.01V               |
| <b>Resolution</b>   | 1 uS/2uS/4uS/8uS/16uS                  | <b>Current range</b>   | *(1/4F.S.) / (F.S.) Adc     |
| <b>Vth1 / Vth2</b>  |  | <b>Measurement range</b>   | *(1/8F.S.) / (1/2F.S.) Ap-p |
| <b>Voltage range</b>  | 5% ~ 95% of reading                    | <b>Resolution</b>  | 0.001/0.01A                 |
| <b>Resolution</b>   | 0.01V/0.01V, 0.001A/0.01A              | <b>Accuracy</b>  | ±5% of (Reading + Range)    |
| <b>Accuracy</b>   | ±2% of (Reading + Range)               | <b>Sampling Rate</b>   | 100KHz                      |
| <b>Noise Measurement</b>  |  | <b>Update Rate</b>   |                             |
| <b>Low Pass Filter</b>  | up to 20 MHz                           | <b>Resolution</b>  | 50~1000 mS                  |
| <b>Voltage range</b>  | 0.6 / 3Vp-p                            | <b>Dimming Measurement</b>   |                             |
| <b>Resolution</b>   | 1mV                                    | <b>Band Width</b>  | 100KHz                      |
| <b>Accuracy</b>   | ±2% OF reading + 5mV                   | <b>Current range</b>   | *(1/8F.S.) / (1/2F.S.) Adc  |
| <b>Over Shoot Measurement</b>   |  | <b>Resolution</b>  |                             |
| <b>Band Width</b>   | 0 ~ 100 KHz                            | 0.001 / 0.01A  |                             |
| <b>Voltage range</b>  | 0 ~ 10 / 30 Vdc                        | <b>Accuracy</b>  | ±5% of (Reading + Range)    |
| <b>Measurement range</b>  | 0 ~ 10 / 30 Vdc                        | <b>Sampling Rate</b>   | 100KHz                      |
| <b>Resolution</b>   | 0.01 Vdc                               | <b>Update Rate</b>   | 50~1000 mS                  |
| <b>Current range</b>  | *(1/4F.S.) / (F.S.) Adc                | <b>Resolution</b>  | 1mS                         |
| <b>Measurement range</b>  | *(1/4F.S.) / (F.S.) Adc                | <b>Frequency range</b>   | 10Hz~35KHz                  |
| <b>Resolution</b>   | 0.001 / 0.01A                          | <b>Resolution</b>  | 1Hz                         |
| <b>Accuracy</b>   | ±1% of (Reading + Range)               | <b>Accuracy</b>  | ±1% of (Reading + Range)    |
| <b>Sampling Rate</b>  | 100KHz                                 | <b>Duty(Ton) Range</b>   | 3uS~90mS                    |
| <b>Update Rate</b>  | 50~1000 mS                             | <b>Resolution</b>  | 1uS                         |
| <b>Resolution</b>   | 1mS                                    | <b>Accuracy</b>  | ±1% of (Reading + Range)    |
| <b>Vpeak Measurement</b>  |  | <b>USB PD Timing Measurement</b>   |                             |
| <b>Vpeak+/Vpeak-</b>  |  | <b>PVT/NVP/Hard Reset/Output Voltage Falling Time</b>  |                             |
| <b>Band Width</b>   | 0 ~ 100 KHz                            | <b>Va/Vb/Vc/Vd</b>   |                             |
| <b>Voltage range</b>  | 0 ~ 10 / 30 Vdc                        | <b>Voltage range</b>   | 0 ~ 10/30 Vdc               |
| <b>Measurement range</b>  | 0 ~ 10 / 30 Vdc                        | <b>Resolution</b>  | 0.01 V                      |
| <b>Resolution</b>   | 0.01 Vdc                               | <b>Accuracy</b>  | 1% of (Reading + Range)     |
| <b>Accuracy</b>   | ±1% of (Reading + Range)               | <b>Timing range</b>  | 3 Sec                       |
| <b>Sampling Rate</b>  | 100KHz                                 | <b>Resolution</b>  | 10 uS                       |
| <b>Update Rate</b>  | 50~1000 mS                             |  |                             |
| <b>Resolution</b>   | 1mS                                    |  |                             |

## 4013A-2 List of Specification and applicable features

| Model  | 4013A Power Meter  |
|--|--|
| <b>No. of Input Channel</b>                                  | <b>2</b>   |
| <b>Applicable test function</b>                              |  |
| 1. Input RMS Current<br>2. Input Frequency<br>3. Input Power | 4. No Load Power Consumption<br>5. Input Power Factor              |
| <b>Specifications</b>  |  |
| <b>ACV meter(Vrms)</b>                                       | 30V / 300V   |
| Resolution   | 16-bit   |
| Accuracy   | ±0.5% of (Reading + Range)   |
| <b>ACA meter(Arms)</b>                                       | 20mA / 200mA / 2A / 20A / 200A(for Inrush)                         |
| Resolution   | 16-bit   |
| Accuracy   | ±0.5% of (Reading + Range) / ±2% of (Reading + Range) (for Inrush) |
| <b>ACW meter</b>   | 0.6W / 6W / 60W / 600W / 6000W                                     |
| Resolution   | 32-bit   |
| Accuracy   | ±0.5% of (Reading + Range)   |
| <b>DCV meter</b>   | 40V / 400V   |
| Resolution   | 0.001V / 0.01V   |
| Accuracy   | ±0.5% of (Reading + Range)   |
| <b>DCA meter</b>   | 20mA / 200mA / 2A / 20A / 200A(for Inrush)                         |
| Resolution   | 0.001mA / 0.01mA / 0.1mA / 1mA / 10mA(for Inrush)                  |
| Accuracy   | ±0.5% of (Reading + Range) / ±2% of (Reading + Range) (for Inrush) |
| <b>DCW meter</b>   | 800mW / 8W / 80W / 800W / 8000W                                    |
| Resolution   | 32-bit   |
| Accuracy   | ±0.5% of (Reading + Range)   |
| <b>PF meter</b>  | ±0.01~1.00   |
| Resolution   | 0.01   |
| Accuracy   | Corresponds to V and A, 1% of (Reading + Range)                    |
| <b>Frequency meter</b>                                       | 40~70 Hz   |
| Resolution   | 0.1 Hz   |
| Accuracy   | ± 0.1 Hz   |
| <b>Inrush Delay/Period</b>                                   | 0~99.9mS/0.1~99.9S   |
| <b>Meter Meas. Rate Interval time</b>                        | 100mS / 200mS / 500mS / 1S / 5S / 10S                              |
| <b>Low Pass Filter(V &amp; A)</b>                            | 50KHz  |
| <b>Interface</b>   | RS-232   |

## 4015A-2 List of Specification and applicable features

| Model                           | 4015A-2 Power Meter With Harmonic |   |               |              |
|---------------------------------|-----------------------------------|---|---------------|--------------|
| No. of Input Channel            | 2                                 |   |               |              |
| <b>Applicable test function</b> |                                   |   |               |              |
| 1. Input RMS Current            |                                   | 4. No Load Power Consumption  |               |              |
| 2. Input Frequency              |                                   | 5. Input Power Factor   |               |              |
| 3. Input Power                  |                                   | 6. Current Harmonic   |               |              |
| <b>Specifications</b>           |                                   |   |               |              |
| ACV meter (Vrms)                | Range                             | 15V / 0.001V, 30V / 0.001V, 50V / 0.01V<br>150V / 0.01V, 300V / 0.01V, 500V / 0.1V  |               |              |
|                                 | Accuracy                          | ±0.1% of (Reading + Range)  |               |              |
| ACA meter (Arms)                | Range                             | 20mA / 0.001mA, 500mA / 0.01mA, 10A / 1mA<br>50mA / 0.001mA, 2A / 0.1mA, 20A / 1mA<br>200mA / 0.01mA, 5A / 0.1mA, 200A peak / 0.01A |               |              |
|                                 | Accuracy                          | ±0.1% of (Reading + Range)  |               |              |
|                                 |                                   | ±2% of (Reading + Range, for Inrush)  |               |              |
| ACW meter                       | Range                             | 0.3W / 0.01mW   | 0.6W / 0.01mW | 1W / 0.1mW   |
|                                 |                                   | 0.75W / 0.1mW   | 1.5W / 0.1mW  | 2.5W / 0.1mW |
|                                 | 3W / 0.1mW                        | 6W / 0.1mW  | 10W / 1mW     |              |
|                                 |                                   | 7.5W / 1mW  | 15W / 1mW     | 25W / 1mW    |
|                                 |                                   | 30W / 1mW   | 60W / 1mW     | 100W / 10mW  |
|                                 |                                   | 75W / 1mW   | 150W / 10mW   | 250W / 10mW  |
|                                 |                                   | 150W / 10mW   | 300W / 10mW   | 500W / 10mW  |
|                                 |                                   | 300W / 10mW   | 600W / 10mW   | 1000W / 0.1W |
|                                 |                                   | 3W / 0.1mW  | 6W / 0.1mW    | 10W / 1mW    |
|                                 |                                   | 7.5W / 1mW  | 15W / 1mW     | 25W / 1mW    |
|                                 |                                   | 30W / 1mW   | 60W/1mW       | 100W / 10mW  |
|                                 |                                   | 75W / 10mW  | 150W / 10mW   | 250W / 10mW  |
|                                 |                                   | 300W / 10mW   | 600W / 10mW   | 1000W / 0.1W |
|                                 |                                   | 750W / 10mW   | 1500W / 0.1W  | 2500W / 0.1W |
|                                 |                                   | 1500W / 0.1W  | 3000W / 0.1W  | 5000W / 0.1W |
|                                 |                                   | 3000W / 0.1W  | 6000W / 0.1W  | 10000W / 1W  |
|                                 | Accuracy                          | ±0.1% of (Reading + Range)  |               |              |
| DCV                             | Range                             | Same as AC  |               |              |
|                                 | Accuracy                          | Same as AC  |               |              |
| DCA                             | Range                             | Same as AC  |               |              |
|                                 | Accuracy                          | Same as AC  |               |              |
| DCW                             | Range                             | Same as AC  |               |              |
|                                 | Accuracy                          | Same as AC  |               |              |
| PF meter                        | Range                             | ±0.001~1.000 / 0.001  |               |              |
|                                 | Accuracy                          | 1% of (Reading + Range, Corresponds to V and A)   |               |              |
| Frequency meter                 | Range                             | 40~70 / 0.1Hz   |               |              |
|                                 | Accuracy                          | ± 0.1 Hz  |               |              |
| V/A                             | Number                            | 1~50 th / Same as ACV, ACA meter  |               |              |
| Harmonic                        | Accuracy                          | ±0.5% of (Reading + Range)  |               |              |
| V/A THD                         | Range                             | 0%~255% / 0.001%  |               |              |
|                                 | Accuracy                          | ±0.5% of (Reading + Range)  |               |              |
| Inrush Delay / Period           |                                   | 0~100ms   |               |              |
| Low Pass Filter(V & A)          |                                   | 50KHz   |               |              |
| Interface                       |                                   | RS-232  |               |              |

### 5303 AVR Suitable test item & Specifications

|                           |                            |
|---------------------------|----------------------------|
| Model                     | 5303 AVR                   |
| <b>Suitable Test Item</b> |                            |
| 1. Input Inrush Current   |                            |
| <b>Specifications</b>     |                            |
| Power Rating              | 3KVA                       |
| Maximum Capacity          | CF > 7                     |
| Input Voltage Rating      | 230Vrms +/- 10%            |
| Output Voltage Rating     | 230,264,277Vrms Selectable |
| Accuracy                  | ±2.5Vrms                   |
| Interface                 | RS-232 remote control only |

### PFR-100L/100M Suitable test item & Specifications

|                            |                                       |          |
|----------------------------|---------------------------------------|----------|
| Model                      | Fanless Multi-Range D.C. Power Supply |          |
| <b>Suitable Test Item</b>  |                                       |          |
| 1. Over Voltage Protection |                                       |          |
| <b>Specifications</b>      | PFR-100L                              | PFR-100M |
| Power Rating               | 100W                                  |          |
| Voltage range              | 0 ~ 50V                               | 0 ~ 250V |
| Resolution                 | 40mV                                  | 200mV    |
| Current range              | 0 ~ 10A                               | 0 ~ 2A   |
| Resolution                 | 1mA                                   | 0.1mA    |
| Slew rate                  | Rise Time                             | 50ms     |
|                            | Fall Time                             | 100ms    |
| Protection                 | OCP , OTP                             |          |

### 99094-2 List of Specification and applicable features

|   |                                   |
|---|-----------------------------------|
| Model   | 99094-2 Quick Charge Controller   |
| <b>Applicable test function</b>   |                                   |
| <ol style="list-style-type: none"> <li>1. USB PD Source / Sink Profile</li> <li>2. USB PD Power Data Object (PDO)</li> <li>3. USB PD Output Voltage Change</li> <li>4. USB Type C Cable Unplug</li> </ol> |                                   |
| <b>Specifications</b>   |                                   |
| No. of Test Channel   | 2                                 |
| Support Quick Charge  | QC2.0, QC3.0, PE+, PE+2.0, USB PD |
| Terminal of Charger   | D-sub 15Pin for ChxA, ChxB        |

## Order Information



### Basic version

6050-2-A1 ( 3332F )  
USB PD Dual-channel Test System



### Standard version

6050-2-B1 ( 3332F )  
USB PD Dual-channel Test System



### Value version

6050-2-C1 ( 3332F )  
USB PD Dual-channel Test System



### Complete version

6050-2-D1 ( 3332F )  
USB PD Dual-channel Test System