NO. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan www.gwinstek.com

T (886) 2 2268-0389 F (886)2 2268-0639

## PPS-3635 Specifications

The specifications apply when the PPS-3635 is powered on for at least 30 minutes under +20°C~+30°C.

OUTPUT

0~36V Voltage Current 0~3.5A OVP 0~38.5V

LOAD REGULATION

Voltage ≤ 3mV rear output ( ≤ 6mV front output ) Current  $\leq$  3mA (  $\leq$  6mA rating current > 3.5A)

LINE REGULATION

Voltage < 3mV Current ≤ 3mA

**RESOLUTION** 

10mV (20mV rating voltage > 36V) Voltage Current 1mA (2mA rating current >3.5A) OVP 10mV(20mV rating voltage > 36V)

PROGRAM ACCURACY (25±5°C)

Voltage  $\leq$  0.05% + 25mV ( + 50mV rating voltage > 36 V )

≤ 0.2% + 10mA Current OVP ≤ 2% + 0.6V

RIPPLE & NOISE (20Hz ~ 20MHz)

Voltage Ripple 1mVrms / 3mVp-p

Noise 2mVrms / 30mVp-p

Current  $\leq$  3mA rms ( $\leq$  5mA rms rating current > 3.5A)

TEMPERATURE (0~40° C) COEFFICIENT

Voltage < 100ppm + 3mV</p> Current < 150ppm + 3mA

READBACK RESOLUTION

Voltage 10mV (20mV rating voltage > 36V) Current 1mA (2mA rating current > 3.5A)

READBACK ACCURACY (25±5°C)

Voltage  $\leq$  0.05% + 25mV ( + 50mV rating voltage > 36V)

Current < 0.2% + 10mA

**RESPONSE TIME** 

Voltage Up(10%~90%) ≤ 100mS Voltage Down(90%~10%) < 100mS

READBACK TEMPERATURE COEFFICIENT

Voltage  $\leq$  100ppm + 10mV ( + 20mV rating voltage > 36V)

Current 150ppm + 10mA

DRIFT

Voltage < 0.03% + 6mV

## GOOD WILL INSTRUMENT CO., LTD.

**GWINSTEK** 

N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

Current	≤ 0.1% + 6mA
MEMORY	
	Store / Recall 100 sets
TIMER	
Setting time	1 sec ~ 255 Min ( Max 255 Min x 100 sets)
Resolution	1 sec
Function	for output working loop ( Auto Step Running)
INTERFACE	
	GPIB Interface Standard
POWER SOURCE	
	AC100V/120V/220V/240V±10%, 50/60Hz
ACCESSORIES	
	User manual x 1
	Power cord x 1
	Test lead GTL-104 x 1
DIMENSIONS & WEIGHT	
	255(W) x 145(H) x 346(D)mm
	Approx. 9.5 kg